

Richerlink Onu Firmware Upgrade

1. Connect Onu With Lan Cable And Type 192.168.1.1 In Browser And Login



Username:

Password:

Password:- ONU@xxxx
Xxxx Is The Last 4 digit Of
Onu Mac Address In Small

In URL Remove Content.asp and Type upgrade.asp and press enter

The screenshot shows a web browser window with the address bar containing the URL `192.168.1.1/cgi-bin/upgrade.asp`. The page header features the **RicherLink** logo and the Chinese characters **瑞吉联**. A navigation bar includes a **Status** menu and tabs for **Status**, **Network**, **Security**, **Application**, **Maintenance**, and **Diagnosis**. The **Status** tab is active, displaying a table of basic information. A **HELP** button is visible on the right side of the page.

Basic Information	
PON AccessType:	Unknown
Device Model:	RL821GWV
Device ID:	1C184A-1C184ABA5510
Hardware Version:	V2.0
Software Version:	V2.0.5-27878
RunTime:	00:00:05:02
CurrentTime:	1970/01/01 00:05
WanUp Time:	00:00:00:00
PonOnline Time:	00:00:00:00

- 1- Click On Choose File and Select the Firmware
- 2- Click On Apply And wait for 60 Seconds
- 3- Don't Remove or turn off the Onu ! Your firmware will be upgrade Soon

The screenshot shows a web browser window with the title 'FW Upgrade' and the address bar displaying '192.168.1.1/cgi-bin/upgrade.asp'. The page features the RicherLink logo (瑞吉联) in the top left and a 'Welcome!' message with a 'Back to Homepage' link in the top right. A left sidebar contains an 'Upgrade Management' section. The main content area includes a file selection interface with radio buttons for 'romfile' and 'tclinux.bin', a 'Choose File' button, and a 'ROMFILE BACKUP' button. A red note at the bottom states: 'Note: It might take several minutes, don't power off it during upgrading. Device will restart after the upgrade.'